



## NC-X700 is a powerful visual communication hub that transforms any display into a collaboration screen and a digital announcement board

With the NovoConnect NC-X700, meeting participants are able to mirror or wirelessly show content from any device to a larger display screen. Thanks to the cross-platform compatibility with Windows, macOS, Ubuntu, Android and iOS, the connection is smooth and easy. In addition, users can make a direct connection to the Windows 10 Miracast. Guests will benefit from an optional LauncherPlus USB, which is an extension for direct WiFi connectivity from any laptop. Furthermore The NC-X700 offers a seamless switch to Digital Signage mode in between meetings and transform idle screens into digital announcement boards.

### Features

- Wireless collaboration & digital signage integrated
- Windows 10 Miracast screen mirroring
- Split screen functionality for up to four sources to share simultaneously
- Ability to receive NT LiveScreen data for display duplication in real-time
- Cross-platform compatibility with Windows, macOS, Ubuntu, Android and iOS
- Supports 4K display resolution
- Dual-Video Decoding enables two videos decode simultaneously when used in digital signage mode
- AES 256 encryption for data protection
- PIN-protected guest access
- Dual network setting to separate guest and employee network



MODEL		NC-X700
BYOD	BYOD - Supported OS	Windows 7 / 8 / 10 (32 bits and 64 bits), macOS 10.7 and above, Ubuntu 18.04 and above, iOS 11.0 and above, Android 5.0 and above
		Screen Mirroring for iOS and Android
		Windows 10 Miracast
	Split Screen	Up to 4, in dynamic layout
	Mirroring Resolution	Up to 4K-UHD, 30 fps
FEATURES	Output Resolution	4K-UHD (3840 x 2160), 1080p (1920 x 1080), 720p (1280 x 720)
	Collaboration	Windows 10 Extended Desktop function, Moderator function, AirNote for instant annotation from meeting participants, Novo Screennote for virtual whiteboard and NovoConnect app
	Productivity	Meeting ID, QR Code connection support, PIN connection function
	Digital Signage	NovoDS Digital Signage - Message and Announcement Board, intuitive drag-and-drop interface, flexible playlist creation, dynamic content from text, audio, photos and videos to webpages, Twitter, RSS, Google Calendar, Weather, and more
	Screen Duplication Over the Network	NT Live Receiver for wireless screen duplication
CONNECTIVITY	Security	Dual network WiFi & LAN, AES-256 encryption, ISO 27001, Kensington lock
	WiFi	802.11ac, b/g/n, 2.4GHz & 5GHz 2T2R with 2 external antenna
	Output	HDMI-Out Audio-Out (3.5mm jack)
	Input	Ethernet RJ45, USB Type A x 1, USB Type C x 1, microSD Slot, RS-232 jack, DC Jack Power-In
SYSTEM	CPU	Six-core ARM
	Storage	16GB
GENERAL	Power	Input to AC adapter: AC 100-240V, 50/60Hz. Output from AC adapter: 5V/3A. Consumption: 15W
	Product Dimensions (L x W x H)	151 x 117 x 24.7 mm
	Weight (Net)	270 g
	What's Included	Main Unit, 2x Antennas, HDMI Cable, USB Cable, Power Adapter, Remote Control with Batteries, Wall Mount KIT, Document KIT
	Optional Accessory	LauncherPlus(WQL-400), LauncherOne and NovoDS Cloud licence
	Warranty	3 Years

### NC-X700 Connectivity



### LauncherPlus Functionality

Optional Plug-and-Play Launcher for guest and team members to instantly connect to the NovoConnect unit from a laptop.

